

SMART DIGITAL MULTIMETER

074 A

PROMO



- SMART function: automatically selects AC/DC voltage, resistance, frequency
- AC/DC measurement
- Resistance and continuity measurements (acoustic sound if circuit resistance is lower than 40 to Ω)
- Frequency measurements
- AC/DC current measurement with 076 P ammeter
- HOLD key: locks the displayed value
- MAX/MIN key: to display the minimum and maximum value between the measured data
- Digital display with backlight
- Automatic switch off after 15 minutes
- Battery charge status indicator
- Supplied with a pair of insulated tips and case
- CAT III 600 V

Direct voltage DC (mV÷V)	1÷600
Frequency kHz	3÷40
Resistance (Ω ÷M Ω)	0÷10
Alternating voltage AC (mV÷V)	1÷600
Battery type (supplied)	2xAAA

Family details

Code	LxPxH mm	Weight gr	Quantity for packaging
U00740001	152x72x45	230	1

Stanley Black & Decker Italia S.r.l.

Sede legale: Via Energy Park 6 - 20871 Vimercate (MB)
 Sede operativa: Via Volta 3 - 21020 Monvalle (VA) Italia
 Partita IVA e C.F.: 03225990138

StanleyBlack&Decker

Società a Socio Unico soggetta a coord. e controllo da parte di Stanley Black & Decker, Inc.
 Capitale Sociale I.V. € 12.000.000