

PROFESSIONAL START BOOSTER 12 V, PORTABLE

1613 RA12

PROMO



- For intensive professional use
- Emergency starter suitable for 12V motorcycles, cars, vans and commercial vehicles
- Long cables (155 cm) that allow the use of the starter from the ground
- Integrated transformer: no external power supply
- High performance pure lead AGM battery
- LED indicator of the charge status of the starter's internal battery
- To check the state of charge of the vehicle battery, connect the cables and press the TEST button (Red: battery to be recharged/replaced immediately; Yellow: Battery almost empty; Green: Battery full)
- External fuse: overcurrent protection up to 300A
- Straight clamps
- Shockproof ABS shell
- Also suitable for sealed batteries
- Supplied with mins charger (for optimal charging, it is recommended to connect the power plug to a direct power source; avoid multiple sockets)

Battery type (supplied)	AGM
Cable section (mm ²)	21,5
Cable length (cm)	155
Pliers amperage (A)	1000
Starting current (A)	3500
Working current (A)	1200
Working voltage (V)	12



Family details

Stanley Black & Decker Italia S.r.l.

Sede legale: Via Energy Park 6 - 20871 Vimercate (MB)
Sede operativa: Via Volta 3 - 21020 Monvalle (VA) Italia
Partita IVA e C.F.: 03225990138

StanleyBlack&Decker

Società a Socio Unico soggetta a coord. e controllo da parte di Stanley Black & Decker, Inc.
Capitale Sociale I.V. € 12.000.000

Code	LxPxH mm	 Weight kg	 Quantity for packaging
U16130019	400x115x320	10	1

Stanley Black & Decker Italia S.r.l.

Sede legale: Via Energy Park 6 - 20871 Vimercate (MB)
Sede operativa: Via Volta 3 - 21020 Monvalle (VA) Italia
Partita IVA e C.F.: 03225990138

StanleyBlack&Decker

Società a Socio Unico soggetta a coord. e controllo
da parte di Stanley Black & Decker, Inc.
Capitale Sociale I.V. € 12.000.000